



Fuse switch disconnecter, 4p, NH2, AC22

**Part no.** PIFT2L431C401CCA  
**Catalog No.** 160620  
**Alternate Catalog No.** PIFT2L431C401CCA

**Technical data ETIM 8.0**

|   |    |                     |
|---|----|---------------------|
| Low-voltage industrial components (EG000017) / Fuse switch disconnecter (EC001040)  |    |                     |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Fuse switch disconnecter (ec@ss10.0.1-27-37-14-01 [AKF058013]) |    |                     |
| Version as main switch  |    | No                  |
| Version as safety switch  |    | No                  |
| Max. rated operation voltage Ue AC  | V  | 690                 |
| Rated permanent current Iu  | A  | 400                 |
| Rated operation power at AC-23, 400 V   | kW | 0                   |
| Conditioned rated short-circuit current Iq  | kA | 55                  |
| Rated short-time withstand current Icw  | kA | 0                   |
| Suitable for fuses  |    | NH2                 |
| Number of poles   |    | 4                   |
| With error protection   |    | Yes                 |
| Type of electrical connection of main circuit   |    | Screw connection    |
| Cable entry   |    | Side                |
| Equipped with connectors  |    | Yes                 |
| Suitable for floor mounting   |    | No                  |
| Suitable for front mounting   |    | Yes                 |
| Suitable for busbar mounting  |    | No                  |
| Type of control element   |    | Long turning handle |
| Position control element  |    | Front side          |
| Motor drive optional  |    | Yes                 |
| Motor drive integrated  |    | No                  |
| Version as emergency stop installation  |    | No                  |
| Degree of protection (IP), front side   |    | IP40                |

**Additional product information (links)**

|                          |   |
|--------------------------|---|
| Instruction leaflet PIFT | <a href="https://es-assets.eaton.com/ENGINEERING/CONFIGURATOR/XENERGY/IL-PIFT-01M-2018-08.pdf">https://es-assets.eaton.com/ENGINEERING/CONFIGURATOR/XENERGY/IL-PIFT-01M-2018-08.pdf</a> |
|--------------------------|---|